

**Table 3-1** Summary of vector relations.

	Cartesian Coordinates	Cylindrical Coordinates	Spherical Coordinates
<b>Coordinate variables</b>	$x, y, z$	$r, \phi, z$	$R, \theta, \phi$
<b>Vector representation</b> $\mathbf{A} =$	$\hat{x}A_x + \hat{y}A_y + \hat{z}A_z$	$\hat{r}A_r + \hat{\phi}A_\phi + \hat{z}A_z$	$\hat{R}A_R + \hat{\theta}A_\theta + \hat{\phi}A_\phi$
<b>Magnitude of A</b> $ \mathbf{A}  =$	$\sqrt{A_x^2 + A_y^2 + A_z^2}$	$\sqrt{A_r^2 + A_\phi^2 + A_z^2}$	$\sqrt{A_R^2 + A_\theta^2 + A_\phi^2}$
<b>Position vector</b> $\overrightarrow{OP_1} =$	$\hat{x}x_1 + \hat{y}y_1 + \hat{z}z_1,$ for $P(x_1, y_1, z_1)$	$\hat{r}r_1 + \hat{z}z_1,$ for $P(r_1, \phi_1, z_1)$	$\hat{R}R_1,$ for $P(R_1, \theta_1, \phi_1)$
<b>Base vectors properties</b>	$\hat{x} \cdot \hat{x} = \hat{y} \cdot \hat{y} = \hat{z} \cdot \hat{z} = 1$ $\hat{x} \cdot \hat{y} = \hat{y} \cdot \hat{z} = \hat{z} \cdot \hat{x} = 0$ $\hat{x} \times \hat{y} = \hat{z}$ $\hat{y} \times \hat{z} = \hat{x}$ $\hat{z} \times \hat{x} = \hat{y}$	$\hat{r} \cdot \hat{r} = \hat{\phi} \cdot \hat{\phi} = \hat{z} \cdot \hat{z} = 1$ $\hat{r} \cdot \hat{\phi} = \hat{\phi} \cdot \hat{z} = \hat{z} \cdot \hat{r} = 0$ $\hat{r} \times \hat{\phi} = \hat{z}$ $\hat{\phi} \times \hat{z} = \hat{r}$ $\hat{z} \times \hat{r} = \hat{\phi}$	$\hat{R} \cdot \hat{R} = \hat{\theta} \cdot \hat{\theta} = \hat{\phi} \cdot \hat{\phi} = 1$ $\hat{R} \cdot \hat{\theta} = \hat{\theta} \cdot \hat{\phi} = \hat{\phi} \cdot \hat{R} = 0$ $\hat{R} \times \hat{\theta} = \hat{\phi}$ $\hat{\theta} \times \hat{\phi} = \hat{R}$ $\hat{\phi} \times \hat{R} = \hat{\theta}$
<b>Dot product</b> $\mathbf{A} \cdot \mathbf{B} =$	$A_x B_x + A_y B_y + A_z B_z$	$A_r B_r + A_\phi B_\phi + A_z B_z$	$A_R B_R + A_\theta B_\theta + A_\phi B_\phi$
<b>Cross product</b> $\mathbf{A} \times \mathbf{B} =$	$\begin{vmatrix} \hat{x} & \hat{y} & \hat{z} \\ A_x & A_y & A_z \\ B_x & B_y & B_z \end{vmatrix}$	$\begin{vmatrix} \hat{r} & \hat{\phi} & \hat{z} \\ A_r & A_\phi & A_z \\ B_r & B_\phi & B_z \end{vmatrix}$	$\begin{vmatrix} \hat{R} & \hat{\theta} & \hat{\phi} \\ A_R & A_\theta & A_\phi \\ B_R & B_\theta & B_\phi \end{vmatrix}$
<b>Differential length</b> $d\mathbf{l} =$	$\hat{x} dx + \hat{y} dy + \hat{z} dz$	$\hat{r} dr + \hat{\phi} r d\phi + \hat{z} dz$	$\hat{R} dR + \hat{\theta} R d\theta + \hat{\phi} R \sin \theta d\phi$
<b>Differential surface areas</b>	$ds_x = \hat{x} dy dz$ $ds_y = \hat{y} dx dz$ $ds_z = \hat{z} dx dy$	$ds_r = \hat{r} r d\phi dz$ $ds_\phi = \hat{\phi} dr dz$ $ds_z = \hat{z} r dr d\phi$	$ds_R = \hat{R} R^2 \sin \theta d\theta d\phi$ $ds_\theta = \hat{\theta} R \sin \theta dR d\phi$ $ds_\phi = \hat{\phi} R dR d\theta$
<b>Differential volume</b> $dV =$	$dx dy dz$	$r dr d\phi dz$	$R^2 \sin \theta dR d\theta d\phi$

**Table 3-2** Coordinate transformation relations.

Transformation	Coordinate Variables	Unit Vectors	Vector Components
<b>Cartesian to cylindrical</b>	$r = \sqrt{x^2 + y^2}$ $\phi = \tan^{-1}(y/x)$ $z = z$	$\hat{r} = \hat{x} \cos \phi + \hat{y} \sin \phi$ $\hat{\phi} = -\hat{x} \sin \phi + \hat{y} \cos \phi$ $\hat{z} = \hat{z}$	$A_r = A_x \cos \phi + A_y \sin \phi$ $A_\phi = -A_x \sin \phi + A_y \cos \phi$ $A_z = A_z$
<b>Cylindrical to Cartesian</b>	$x = r \cos \phi$ $y = r \sin \phi$ $z = z$	$\hat{x} = \hat{r} \cos \phi - \hat{\phi} \sin \phi$ $\hat{y} = \hat{r} \sin \phi + \hat{\phi} \cos \phi$ $\hat{z} = \hat{z}$	$A_x = A_r \cos \phi - A_\phi \sin \phi$ $A_y = A_r \sin \phi + A_\phi \cos \phi$ $A_z = A_z$
<b>Cartesian to spherical</b>	$R = \sqrt{x^2 + y^2 + z^2}$ $\theta = \tan^{-1}[\sqrt{x^2 + y^2}/z]$ $\phi = \tan^{-1}(y/x)$	$\hat{R} = \hat{x} \sin \theta \cos \phi + \hat{y} \sin \theta \sin \phi + \hat{z} \cos \theta$ $\hat{\theta} = \hat{x} \cos \theta \cos \phi + \hat{y} \cos \theta \sin \phi - \hat{z} \sin \theta$ $\hat{\phi} = -\hat{x} \sin \phi + \hat{y} \cos \phi$	$A_R = A_x \sin \theta \cos \phi + A_y \sin \theta \sin \phi + A_z \cos \theta$ $A_\theta = A_x \cos \theta \cos \phi + A_y \cos \theta \sin \phi - A_z \sin \theta$ $A_\phi = -A_x \sin \phi + A_y \cos \phi$
<b>Spherical to Cartesian</b>	$x = R \sin \theta \cos \phi$ $y = R \sin \theta \sin \phi$ $z = R \cos \theta$	$\hat{x} = \hat{R} \sin \theta \cos \phi + \hat{\theta} \cos \theta \cos \phi - \hat{\phi} \sin \phi$ $\hat{y} = \hat{R} \sin \theta \sin \phi + \hat{\theta} \cos \theta \sin \phi + \hat{\phi} \cos \phi$ $\hat{z} = \hat{R} \cos \theta - \hat{\theta} \sin \theta$	$A_x = A_R \sin \theta \cos \phi + A_\theta \cos \theta \cos \phi - A_\phi \sin \phi$ $A_y = A_R \sin \theta \sin \phi + A_\theta \cos \theta \sin \phi + A_\phi \cos \phi$ $A_z = A_R \cos \theta - A_\theta \sin \theta$
<b>Cylindrical to spherical</b>	$R = \sqrt{r^2 + z^2}$ $\theta = \tan^{-1}(r/z)$ $\phi = \phi$	$\hat{R} = \hat{r} \sin \theta + \hat{z} \cos \theta$ $\hat{\theta} = \hat{r} \cos \theta - \hat{z} \sin \theta$ $\hat{\phi} = \hat{\phi}$	$A_R = A_r \sin \theta + A_z \cos \theta$ $A_\theta = A_r \cos \theta - A_z \sin \theta$ $A_\phi = A_\phi$
<b>Spherical to cylindrical</b>	$r = R \sin \theta$ $\phi = \phi$ $z = R \cos \theta$	$\hat{r} = \hat{R} \sin \theta + \hat{\theta} \cos \theta$ $\hat{\phi} = \hat{\phi}$ $\hat{z} = \hat{R} \cos \theta - \hat{\theta} \sin \theta$	$A_r = A_R \sin \theta + A_\theta \cos \theta$ $A_\phi = A_\phi$ $A_z = A_R \cos \theta - A_\theta \sin \theta$

## SOME USEFUL VECTOR IDENTITIES

$\mathbf{A} \cdot \mathbf{B} = AB \cos \theta_{AB}$       Scalar (or dot) product  
 $\mathbf{A} \times \mathbf{B} = \hat{\mathbf{n}} AB \sin \theta_{AB}$       Vector (or cross) product,  $\hat{\mathbf{n}}$  normal to plane containing  $\mathbf{A}$  and  $\mathbf{B}$   
 $\mathbf{A} \cdot (\mathbf{B} \times \mathbf{C}) = \mathbf{B} \cdot (\mathbf{C} \times \mathbf{A}) = \mathbf{C} \cdot (\mathbf{A} \times \mathbf{B})$   
 $\mathbf{A} \times (\mathbf{B} \times \mathbf{C}) = \mathbf{B}(\mathbf{A} \cdot \mathbf{C}) - \mathbf{C}(\mathbf{A} \cdot \mathbf{B})$   
 $\nabla(U + V) = \nabla U + \nabla V$   
 $\nabla(UV) = U\nabla V + V\nabla U$   
 $\nabla \cdot (\mathbf{A} + \mathbf{B}) = \nabla \cdot \mathbf{A} + \nabla \cdot \mathbf{B}$   
 $\nabla \cdot (U\mathbf{A}) = U\nabla \cdot \mathbf{A} + \mathbf{A} \cdot \nabla U$   
 $\nabla \times (U\mathbf{A}) = U\nabla \times \mathbf{A} + \nabla U \times \mathbf{A}$   
 $\nabla \times (\mathbf{A} + \mathbf{B}) = \nabla \times \mathbf{A} + \nabla \times \mathbf{B}$   
 $\nabla \cdot (\mathbf{A} \times \mathbf{B}) = \mathbf{B} \cdot (\nabla \times \mathbf{A}) - \mathbf{A} \cdot (\nabla \times \mathbf{B})$   
 $\nabla \cdot (\nabla \times \mathbf{A}) = 0$   
 $\nabla \times \nabla V = 0$   
 $\nabla \cdot \nabla V = \nabla^2 V$   
 $\nabla \times \nabla \times \mathbf{A} = \nabla(\nabla \cdot \mathbf{A}) - \nabla^2 \mathbf{A}$   
 $\int_{\mathcal{V}} (\nabla \cdot \mathbf{A}) d\mathcal{V} = \oint_S \mathbf{A} \cdot d\mathbf{s}$       Divergence theorem ( $S$  encloses  $\mathcal{V}$ )  
 $\int_S (\nabla \times \mathbf{A}) \cdot d\mathbf{s} = \oint_C \mathbf{A} \cdot d\mathbf{l}$       Stokes's theorem ( $S$  bounded by  $C$ )

## GRADIENT, DIVERGENCE, CURL, & LAPLACIAN OPERATORS CARTESIAN (RECTANGULAR) COORDINATES ( $x, y, z$ )

$\nabla V = \hat{\mathbf{x}} \frac{\partial V}{\partial x} + \hat{\mathbf{y}} \frac{\partial V}{\partial y} + \hat{\mathbf{z}} \frac{\partial V}{\partial z}$   
 $\nabla \cdot \mathbf{A} = \frac{\partial A_x}{\partial x} + \frac{\partial A_y}{\partial y} + \frac{\partial A_z}{\partial z}$   
 $\nabla \times \mathbf{A} = \begin{vmatrix} \hat{\mathbf{x}} & \hat{\mathbf{y}} & \hat{\mathbf{z}} \\ \frac{\partial}{\partial x} & \frac{\partial}{\partial y} & \frac{\partial}{\partial z} \\ A_x & A_y & A_z \end{vmatrix} = \hat{\mathbf{x}} \left( \frac{\partial A_z}{\partial y} - \frac{\partial A_y}{\partial z} \right) + \hat{\mathbf{y}} \left( \frac{\partial A_x}{\partial z} - \frac{\partial A_z}{\partial x} \right) + \hat{\mathbf{z}} \left( \frac{\partial A_y}{\partial x} - \frac{\partial A_x}{\partial y} \right)$   
 $\nabla^2 V = \frac{\partial^2 V}{\partial x^2} + \frac{\partial^2 V}{\partial y^2} + \frac{\partial^2 V}{\partial z^2}$

## CYLINDRICAL COORDINATES ( $r, \phi, z$ )

$\nabla V = \hat{\mathbf{r}} \frac{\partial V}{\partial r} + \hat{\phi} \frac{1}{r} \frac{\partial V}{\partial \phi} + \hat{\mathbf{z}} \frac{\partial V}{\partial z}$   
 $\nabla \cdot \mathbf{A} = \frac{1}{r} \frac{\partial}{\partial r} (rA_r) + \frac{1}{r} \frac{\partial A_\phi}{\partial \phi} + \frac{\partial A_z}{\partial z}$   
 $\nabla \times \mathbf{A} = \frac{1}{r} \begin{vmatrix} \hat{\mathbf{r}} & \hat{\phi} & \hat{\mathbf{z}} \\ \frac{\partial}{\partial r} & \frac{\partial}{\partial \phi} & \frac{\partial}{\partial z} \\ A_r & rA_\phi & A_z \end{vmatrix} = \hat{\mathbf{r}} \left( \frac{1}{r} \frac{\partial A_z}{\partial \phi} - \frac{\partial A_\phi}{\partial z} \right) + \hat{\phi} \left( \frac{\partial A_r}{\partial z} - \frac{\partial A_z}{\partial r} \right) + \hat{\mathbf{z}} \frac{1}{r} \left[ \frac{\partial}{\partial r} (rA_\phi) - \frac{\partial A_r}{\partial \phi} \right]$   
 $\nabla^2 V = \frac{1}{r} \frac{\partial}{\partial r} \left( r \frac{\partial V}{\partial r} \right) + \frac{1}{r^2} \frac{\partial^2 V}{\partial \phi^2} + \frac{\partial^2 V}{\partial z^2}$

## SPHERICAL COORDINATES ( $R, \theta, \phi$ )

$\nabla V = \hat{\mathbf{R}} \frac{\partial V}{\partial R} + \hat{\theta} \frac{1}{R} \frac{\partial V}{\partial \theta} + \hat{\phi} \frac{1}{R \sin \theta} \frac{\partial V}{\partial \phi}$   
 $\nabla \cdot \mathbf{A} = \frac{1}{R^2} \frac{\partial}{\partial R} (R^2 A_R) + \frac{1}{R \sin \theta} \frac{\partial}{\partial \theta} (A_\theta \sin \theta) + \frac{1}{R \sin \theta} \frac{\partial A_\phi}{\partial \phi}$   
 $\nabla \times \mathbf{A} = \frac{1}{R^2 \sin \theta} \begin{vmatrix} \hat{\mathbf{R}} & \hat{\theta} & \hat{\phi} \\ \frac{\partial}{\partial R} & \frac{\partial}{\partial \theta} & \frac{\partial}{\partial \phi} \\ A_R & R A_\theta & (R \sin \theta) A_\phi \end{vmatrix}$   
 $= \hat{\mathbf{R}} \frac{1}{R \sin \theta} \left[ \frac{\partial}{\partial \theta} (A_\phi \sin \theta) - \frac{\partial A_\theta}{\partial \phi} \right] + \hat{\theta} \frac{1}{R} \left[ \frac{1}{\sin \theta} \frac{\partial A_R}{\partial \phi} - \frac{\partial}{\partial R} (R A_\phi) \right] + \hat{\phi} \frac{1}{R} \left[ \frac{\partial}{\partial R} (R A_\theta) - \frac{\partial A_R}{\partial \theta} \right]$   
 $\nabla^2 V = \frac{1}{R^2} \frac{\partial}{\partial R} \left( R^2 \frac{\partial V}{\partial R} \right) + \frac{1}{R^2 \sin \theta} \frac{\partial}{\partial \theta} \left( \sin \theta \frac{\partial V}{\partial \theta} \right) + \frac{1}{R^2 \sin^2 \theta} \frac{\partial^2 V}{\partial \phi^2}$

## Mathematical and Physical Models

### Distance between Two Points

$$d = [(x_2 - x_1)^2 + (y_2 - y_1)^2 + (z_2 - z_1)^2]^{1/2}$$

$$d = [r_2^2 + r_1^2 - 2r_1 r_2 \cos(\phi_2 - \phi_1) + (z_2 - z_1)^2]^{1/2}$$

$$d = \{R_2^2 + R_1^2 - 2R_1 R_2 [\cos \theta_2 \cos \theta_1 + \sin \theta_1 \sin \theta_2 \cos(\phi_2 - \phi_1)]\}^{1/2}$$

### Coordinate Systems Table 3-1

### Coordinate Transformations Table 3-2

### Vector Products

$$\mathbf{A} \cdot \mathbf{B} = AB \cos \theta_{AB}$$

$$\mathbf{A} \times \mathbf{B} = \hat{\mathbf{n}} AB \sin \theta_{AB}$$

$$\mathbf{A} \cdot (\mathbf{B} \times \mathbf{C}) = \mathbf{B} \cdot (\mathbf{C} \times \mathbf{A}) = \mathbf{C} \cdot (\mathbf{A} \times \mathbf{B})$$

$$\mathbf{A} \times (\mathbf{B} \times \mathbf{C}) = \mathbf{B}(\mathbf{A} \cdot \mathbf{C}) - \mathbf{C}(\mathbf{A} \cdot \mathbf{B})$$

### Divergence Theorem

$$\int_V \nabla \cdot \mathbf{E} dV = \oint_S \mathbf{E} \cdot d\mathbf{s}$$

### Vector Operators

$$\nabla T = \hat{\mathbf{x}} \frac{\partial T}{\partial x} + \hat{\mathbf{y}} \frac{\partial T}{\partial y} + \hat{\mathbf{z}} \frac{\partial T}{\partial z}$$

$$\nabla \cdot \mathbf{E} = \frac{\partial E_x}{\partial x} + \frac{\partial E_y}{\partial y} + \frac{\partial E_z}{\partial z}$$

$$\nabla \times \mathbf{B} = \hat{\mathbf{x}} \left( \frac{\partial B_z}{\partial y} - \frac{\partial B_y}{\partial z} \right) + \hat{\mathbf{y}} \left( \frac{\partial B_x}{\partial z} - \frac{\partial B_z}{\partial x} \right) + \hat{\mathbf{z}} \left( \frac{\partial B_y}{\partial x} - \frac{\partial B_x}{\partial y} \right)$$

$$\nabla^2 V = \frac{\partial^2 V}{\partial x^2} + \frac{\partial^2 V}{\partial y^2} + \frac{\partial^2 V}{\partial z^2}$$

(see back cover for cylindrical and spherical coordinates)

### Stokes's Theorem

$$\int_S (\nabla \times \mathbf{B}) \cdot d\mathbf{s} = \oint_C \mathbf{B} \cdot d\mathbf{l}$$

## Mathematical and Physical Models

### Maxwell's Equations for Electrostatics

Name	Differential Form	Integral Form
Gauss's law	$\nabla \cdot \mathbf{D} = \rho_v$	$\oint_S \mathbf{D} \cdot d\mathbf{s} = Q$
Kirchhoff's law	$\nabla \times \mathbf{E} = 0$	$\oint_C \mathbf{E} \cdot d\mathbf{l} = 0$

### Electric Field

Current density  $\mathbf{J} = \rho_v \mathbf{u}$

Poisson's equation  $\nabla^2 V = -\frac{\rho_v}{\epsilon}$

Laplace's equation  $\nabla^2 V = 0$

Resistance  $R = \frac{l}{\int_S \sigma \mathbf{E} \cdot d\mathbf{s}}$

### Boundary conditions Table 4-3

Capacitance  $C = \frac{\int_S \epsilon \mathbf{E} \cdot d\mathbf{s}}{-\int_l \mathbf{E} \cdot d\mathbf{l}}$

RC relation  $RC = \frac{\epsilon}{\sigma}$

Energy density  $w_e = \frac{1}{2} \epsilon E^2$

Point charge

$$\mathbf{E} = \hat{\mathbf{R}} \frac{q}{4\pi \epsilon R^2}$$

Many point charges

$$\mathbf{E} = \frac{1}{4\pi \epsilon} \sum_{i=1}^N \frac{q_i (\mathbf{R} - \mathbf{R}_i)}{|\mathbf{R} - \mathbf{R}_i|^3}$$

Volume distribution

$$\mathbf{E} = \frac{1}{4\pi \epsilon} \int_V \hat{\mathbf{R}}' \frac{\rho_v dV'}{R'^2}$$

Surface distribution

$$\mathbf{E} = \frac{1}{4\pi \epsilon} \int_{S'} \hat{\mathbf{R}}' \frac{\rho_s ds'}{R'^2}$$

Line distribution

$$\mathbf{E} = \frac{1}{4\pi \epsilon} \int_{l'} \hat{\mathbf{R}}' \frac{\rho_l dl'}{R'^2}$$

Infinite sheet of charge

$$\mathbf{E} = \hat{\mathbf{z}} \frac{\rho_s}{2\epsilon_0}$$

Infinite line of charge

$$\mathbf{E} = \frac{\mathbf{D}}{\epsilon_0} = \hat{\mathbf{r}} \frac{D_r}{\epsilon_0} = \hat{\mathbf{r}} \frac{\rho_l}{2\pi \epsilon_0 r}$$

Dipole

$$\mathbf{E} = \frac{qd}{4\pi \epsilon_0 R^3} (\hat{\mathbf{R}} 2 \cos \theta + \hat{\boldsymbol{\theta}} \sin \theta)$$

Relation to V

$$\mathbf{E} = -\nabla V$$

$$I = \int_S \mathbf{J} \cdot d\mathbf{s} \quad (\text{A}). \quad (4.12)$$

$$V_{21} = V_2 - V_1 = - \int_{P_1}^{P_2} \mathbf{E} \cdot d\mathbf{l}, \quad (4.39)$$

$$V = \frac{1}{4\pi\epsilon} \int_{V'} \frac{\rho_v}{R'} dV' \quad (\text{volume distribution}), \quad (4.48a)$$

$$V = \frac{1}{4\pi\epsilon} \int_{S'} \frac{\rho_s}{R'} ds' \quad (\text{surface distribution}), \quad (4.48b)$$

$$V = \frac{1}{4\pi\epsilon} \int_{l'} \frac{\rho_l}{R'} dl' \quad (\text{line distribution}). \quad (4.48c)$$

$$\mathbf{J} = \sigma \mathbf{E} \quad (\text{A/m}^2) \quad (\text{Ohm's law}), \quad (4.63)$$

**Table 4-3** Boundary conditions for the electric fields.

Field Component	Any Two Media	Medium 1 Dielectric $\epsilon_1$	Medium 2 Conductor
<b>Tangential E</b>	$E_{1t} = E_{2t}$	$E_{1t} = E_{2t} = 0$	
<b>Tangential D</b>	$D_{1t}/\epsilon_1 = D_{2t}/\epsilon_2$	$D_{1t} = D_{2t} = 0$	
<b>Normal E</b>	$\epsilon_1 E_{1n} - \epsilon_2 E_{2n} = \rho_s$	$E_{1n} = \rho_s/\epsilon_1$	$E_{2n} = 0$
<b>Normal D</b>	$D_{1n} - D_{2n} = \rho_s$	$D_{1n} = \rho_s$	$D_{2n} = 0$

Notes: (1)  $\rho_s$  is the surface charge density at the boundary; (2) normal components of  $\mathbf{E}_1$ ,  $\mathbf{D}_1$ ,  $\mathbf{E}_2$ , and  $\mathbf{D}_2$  are along  $\hat{\mathbf{n}}_2$ , the outward normal unit vector of medium 2.

## Mathematical and Physical Models

### Maxwell's Magnetostatics Equations

Gauss's Law for Magnetism

$$\nabla \cdot \mathbf{B} = 0 \quad \longleftrightarrow \quad \oint_S \mathbf{B} \cdot d\mathbf{s} = 0$$

Ampère's Law

$$\nabla \times \mathbf{H} = \mathbf{J} \quad \longleftrightarrow \quad \oint_C \mathbf{H} \cdot d\mathbf{l} = I$$

### Lorentz Force on Charge $q$

$$\mathbf{F} = q(\mathbf{E} + \mathbf{u} \times \mathbf{B})$$

### Magnetic Force on Wire

$$\mathbf{F}_m = I \oint_C d\mathbf{l} \times \mathbf{B} \quad (\text{N})$$

### Magnetic Torque on Loop

$$\mathbf{T} = \mathbf{m} \times \mathbf{B} \quad (\text{N}\cdot\text{m})$$

$$\mathbf{m} = \hat{\mathbf{n}} NIA \quad (\text{A}\cdot\text{m}^2)$$

### Biot-Savart Law

$$\mathbf{H} = \frac{I}{4\pi} \int_l \frac{d\mathbf{l} \times \hat{\mathbf{R}}}{R^2} \quad (\text{A/m})$$

### Magnetic Field

Infinitely Long Wire  $\mathbf{B} = \hat{\phi} \frac{\mu_0 I}{2\pi r} \quad (\text{Wb/m}^2)$

Circular Loop  $\mathbf{H} = \hat{z} \frac{Ia^2}{2(a^2 + z^2)^{3/2}} \quad (\text{A/m})$

Solenoid  $\mathbf{B} \approx \hat{z} \mu_0 n I = \frac{\hat{z} \mu_0 N I}{l} \quad (\text{Wb/m}^2)$

### Vector Magnetic Potential

$$\mathbf{B} = \nabla \times \mathbf{A} \quad (\text{Wb/m}^2)$$

### Vector Poisson's Equation

$$\nabla^2 \mathbf{A} = -\mu \mathbf{J}$$

### Inductance

$$L = \frac{\Lambda}{I} = \frac{\Phi}{I} = \frac{1}{I} \int_S \mathbf{B} \cdot d\mathbf{s} \quad (\text{H})$$

### Magnetic Energy Density

$$w_m = \frac{1}{2} \mu H^2 \quad (\text{J/m}^3)$$

**Table 5-1** Attributes of electrostatics and magnetostatics.

Attribute	Electrostatics	Magnetostatics
<b>Sources</b>	Stationary charges $\rho_v$	Steady currents $\mathbf{J}$
<b>Fields and fluxes</b>	$\mathbf{E}$ and $\mathbf{D}$	$\mathbf{H}$ and $\mathbf{B}$
<b>Constitutive parameter(s)</b>	$\epsilon$ and $\sigma$	$\mu$
<b>Governing equations</b>		
• <b>Differential form</b>	$\nabla \cdot \mathbf{D} = \rho_v$ $\nabla \times \mathbf{E} = 0$	$\nabla \cdot \mathbf{B} = 0$ $\nabla \times \mathbf{H} = \mathbf{J}$
• <b>Integral form</b>	$\oint_S \mathbf{D} \cdot d\mathbf{s} = Q$ $\oint_C \mathbf{E} \cdot d\mathbf{l} = 0$	$\oint_S \mathbf{B} \cdot d\mathbf{s} = 0$ $\oint_C \mathbf{H} \cdot d\mathbf{l} = I$
<b>Potential</b>	Scalar $V$ , with $\mathbf{E} = -\nabla V$	Vector $\mathbf{A}$ , with $\mathbf{B} = \nabla \times \mathbf{A}$
<b>Energy density</b>	$w_e = \frac{1}{2}\epsilon E^2$	$w_m = \frac{1}{2}\mu H^2$
<b>Force on charge <math>q</math></b>	$\mathbf{F}_e = q\mathbf{E}$	$\mathbf{F}_m = q\mathbf{u} \times \mathbf{B}$
<b>Circuit element(s)</b>	$C$ and $R$	$L$